

s.QUAD Voice

SWISSPHONE

s.ONE
ready



The Smart Tone & Voice Pager

Swissphone's generation of pagers impresses users with state-of-the-art functional design and unique performance features. Its innovative design makes the s.QUAD Voice extremely robust and very comfortable to wear. Secure receipt of messages and loud alerting take center stage. With a sensitivity of $\leq 2.0 \mu\text{V/m}$, the s.QUAD Voice is the best in its class. The s.QUAD Voice can be updated by firmware to a digital paging receiver (POCSAG), or can work in both modes in parallel as a single device. This option perfectly supports a smooth migration to digital alerting.

s.ONE software solution from Swissphone

Together with the modular s.ONE software solution from Swissphone and a smartphone interface via Bluetooth, the s.QUAD Voice offers additional applications for secure, fast, simple alerting.

- Hybrid alert: Radio alerting combined with IP alerting
- Monitoring: Information on the response of the team
- Resources: Overview of availability
- Reports: Evaluation of the operations at the push of a button

Key performance features

- » Outstanding reception performance
- » Programmable receiving frequency within switching bandwidth. Wide PLL up to 10 MHz
- » 64 addresses (2-tone and 5/6-tone)
- » 64 select as well as toggle profiles available
- » Up to 16 minutes of stored voice memory
- » Alerting volume $> 95 \text{ dB(A)}$ at 1 feet distance
- » Multi-colored alarm LED
- » High-resolution display (for message display via bluetooth)
- » Extremely robust (6.5 feet drop test), dust and water-proof
- » Optional: Multi-channel and scanner
- » Optional: Digital alerting with POCSAG and analogue in one device



	Performance features	Technical data
Standards, compliance, environmental conditions	Standards	ETSI EN 300 296 EN 60068-2-27 (shock) EN 60068-2-6 (vibration) EN 60068-2-32 (6.5 feet drop test) EN 60529 (IP67)
	Temperature range	-4 °F to +131 °F
Main characteristics	Frequency bands <small>(additional frequencies on request)</small>	VHF 2 m band 150-160/146-155/155-164/164-174 MHz UHF 70 cm band 450-460/460-470 MHz
	Frequency processing	PLL, frequency can be adjusted in the entire frequency band with programming software
	Channel spacing	12.5, 20/25 kHz
	Sensitivity* <small>* Typical value at 2 m Band (best position on «salty man»)</small>	Better than 2.0 µV/m
	Signal strength display (RSSI)	5-level display
	Addresses	<ul style="list-style-type: none"> • 64 addresses 2-tone or longtone • 64 address names with eight characters • ZVEI 1 / CCIR1 / free (5/6-tone option)
	Alerting	<ul style="list-style-type: none"> • Volume > 95 dB(A) at 1 feet distance • Vibration alarm • Multi-colored alarm LED, programmable • Up to 64 user profiles or selectable addresses
	Voice Memory	Up to 16 minutes stored voice
Display and housing	Options	Multi-channel (8), 5/6 tone decoding
	Display	<ul style="list-style-type: none"> • Greyscale display with high resolution (146 x 128 pixels, 106 DPI) • White backlight • Displays up to 200 characters per page • Vertical and horizontal menu and font guidance (programmable)
	Dimensions (H x W x D)	3.19 x 2.52 x 0.87 inches
Power management	Weight (including battery)	3.81 oz
	Type of battery	NiMH plus battery or alkaline dry cell (standard AA battery)
	Operating times (eco mode)	<ul style="list-style-type: none"> • Alkaline dry cell (1.5 V): 180 hours • NiMH plus battery (1.2 V/2,000 mAh): 180 hours
	Battery charging time	Four hours
Accessories	Programming set	Programming kit with Windows-based programming software
	Chargers	<ul style="list-style-type: none"> • Charger with relay and antenna connector • Multi-charger
	Carrier bags	<ul style="list-style-type: none"> • Clip holster • Leather case • Safety chain

Specifications are subject to change without notice.



POCSAG Option (Two in One):

s.QUAD Voice works in parallel on the existing analog 2-tone and the future-proof digital POCSAG network. With this software option the s.QUAD pager can receive voice calls and text messages from two different networks. This two-in-one option perfectly supports the migration from analog to digital.



s.ONE ready

s.QUAD was designed to enable the combination of various s.ONE software solutions for clear alerting. Fire Chiefs or Dispatchers can, for example, use their smartphones or computer screens to display how many emergency personnel are available and how many will actually respond.



Bluetooth

Bluetooth technology makes it possible to connect the s.QUAD with a compatible smartphone and ultimately with various s.ONE software solutions from Swissphone. This includes, among other things, the display of the availability of the emergency services and the resources as well as the strength of the team.